



## **STEPHILL GENERATORS LTD      5000LRT**

### **5.0kVA "HIREMAX RANGE PORTABLE PETROL GENERATING SET (3000rpm)**

<b>OUTPUT:</b>	5.0kVA/4.0kW 50Hz, 115/230v, single phase.
<b>CONTROL BOX:</b>	Frame mounted control box comprising 1 x 16a BS4343 & 1 X 32a 115volt, 1 x 16a 230v socket outlets, changeover switch, and re-set button circuit breakers.
<b>ENGINE:</b>	Honda GX270 re-coil start, single cylinder air cooled petrol engine with "oil alert" low oil level shutdown, fitted with fuel tank and exhaust silencer.
<b>ALTERNATOR:</b>	Heavy duty brushless maintenance free, alternator, single bearing.
<b>FUEL TANK:</b>	18.0 litre fuel tank giving with fuel gauge giving 10hours approx. operation at 75% full load
<b>FRAME :</b>	1" heavy duty tubular steel wrap-around frame
<b>MOUNTS:</b>	Angled anti-vibration mounts.
<b>NOISE LEVEL:</b>	71dB (A) @ 7 metres. 96Lwa
<b>DIMENSIONS:</b>	L640mm x W482mm x H600mm
<b>WEIGHT:</b>	66kg (dry).