

Make: Stephill Model: SSP3000

Description: 3kVA Petrol Generator (Silenced)



Petrol generator ideal for use on site or at home to power site lighting, tools and other electrical goods. Capable of producing 110V or 240V output. Lightweight and compact for easy transportation and movement.

Specification - Technical Data

SSP3000 3.0kVA / 2.5KW / HONDA GX200

Standard Features: Honda four stroke engines complete with oil alert and high engine temperature protection / Acoustic steel cabinets with noise levels as low as 62dBA / High efficiency exhaust silencers / Dual voltage output complete with overload protection / Brushless maintenance free alternators

OUTPUT:

3.0kVA / 2.5KW

SOCKETS: BS4343 industrial sockets - 1 x 115V 16A sockets 1 x 230V 16A sockets

ENGINE: HONDA GX200

HP/CYLINDERS: 6.5/1

START: RC

FUEL TANK: 3.6 litres

RUN TIME: 3.2 hours @ 75% Load

NOISE LEVEL: 63dB (A) @ 7 metres. 88LWA

SIZE: L700x W430 x H460mm

WEIGHT: 60kg